



## CREATE SMART LIVING FOR YOU

### Motion Sensor

#### PSP06

- Detects motion using a passive IR sensor
- Farer Range, Faster, Smarter, Thin, Small
- Fitting your home decoration style
- Easy and quick to install
- Extremely low power consumption
- Long battery life, Automatic low battery alerts
- Compatible with any Z-Wave or Z-Wave Plus Controller



S2



#### Specification

|                       |  |
|-----------------------|--|
| Supply Voltage        | DC3.0V by CR123A 1700mAh   |
| RF distance           | Min. 40M indoor<br>100M outdoor line of sight  |
| RF Frequency          | 908.4MHz, 916MHz (U.S. A./Mexico)<br>868.4MHz, 869.85MHz (EU)<br>920.9MHz, 921.7MHz, 923.1MHz (TW/SG/Thai/KR)<br>Transceiver |
| Chip                  | Z-wave 700 Series Module   |
| Battery Life          | 10 years (Alarm Report PIR:50 times/Day, Auto Report: 4 times/ Day, Auto Wake up :1 times/ Day )                             |
| Detect distance       | 10M (@Field of view 100 deg.)  |
| Dimension             | 82 x 25.3 x 23.2mm   |
| Weight                | 21.2g  |
| Location              | indoor use only  |
| Operation Temperature | -20 to 50°C  |
| Operation Humidity    | 85%RH max  |