



CREATE SMART LIVING FOR YOU

PAD18 Z-Wave Dimmer 0-10V

- Secure (S2) inclusion fast, easy install
- Remote and local on/off control of ALL dimmable bulbs using LED drivers with input 0-10 VDC
- Works with push-button (momentary switch) and toggle switch or Potentiometer you can install it behind power sockets
- With Easy Repeater Function
- Z-wave wireless systems integration



Rated Voltage	12-24VDC Max.70mA
V input	Sensor: 0-10 VDC, push-button, Switch, potentiometers 100K
V output	0-10VDC for controller load
RF distance	Min. 40M indoor, 100M outdoor line of sight,
RF Frequency	908.4MHz,916MHz (U.S. A./Mexico) 868.4MHz, 869.85MHz (EU) 920.9MHz, 921.7MHz, 923.1MHz (TW/SG/Thai/KR) Transceiver
Chip	Z-Wave 700 series Module
Dimension	47.5(L) x 39(W) x 15.6(H) mm
Weight	30.2g
Location	indoor use
Operation Temperature	-10 to 40 °C
Operation Humidity	85% RH

