



PSR07 Z-wave Smart Button

- Mult-Function – rotate to control Dimmer percentage
- Adopted The Newest Z-Wave 500 Module
- Built-in Rechargeable Lithium Polymer Battery
- Easy To Install
- Extremely low power consumption
- Simulate Analog Dimmer percentage
- Interactive with other Z-wave Device



Supply Voltage	3.7V (Lithium Polymer Battery)
RF distance	Min. 30M indoor, 100M outdoor line of sight,
RF Frequency	908.4MHz,916MHz (U.S. A./Mexico) 868.4MH, 869.85MHz (EU) 922.5MHz, 923.9MHz, 926.3MHz (JP) Transceiver
Chip	Z-wave 500 Series Module
Battery	220mAh/ 0.5 Years
Dimension	Body Dimension \varnothing 59.7 X 14.9 mm Bracket Dimension \varnothing 71.2 X 10.9 mm
Weight	49.2g
IP classification	indoor use
Operation Temperature	-10 ~ 45°C
Operation Humidity	85%RH max



PHILIO TECHNOLOGY CORPORATION

8F., No. 653-2, Zhongzheng Rd., Xinzhuang Dist., New Taipei City 24257, Taiwan
 sales@philio-tech.com Tel:+886-2-2908-8952 Fax:+886-2-29088652