



PAD07 Z-Wave In-Wall Smart Dimmer

- Wireless dimming on/off control
- Can control 1 Dimmer with 2 real buttons
- Interactive with other Devices
- With Easy Repeater Function
- Z-wave wireless systems integration
- Multi Functions Fitting Your Home Decoration Style



Rated Voltage	100~240V
RF distance	Min. 40M indoor, 100M outdoor line of sight,
RF Frequency	908.4MHz,916MHz (U.S. A./Mexico) 868.4MH, 869.85MHz (EU) 922.5MHz, 923.9MHz, 926.3MHz (JP) Transceiver
Chip	Z-wave 500 Series Module
Output	
Current	0.9A
Load	200W(230VAC)/100W(100VAC)
Dimension	47.5(L) x 39(W) x 16(H) mm
Weight	52g
IP classification	indoor use
Operation Temperature	0 ~ 40°C
Operation Humidity	85%RH max



PHILIO TECHNOLOGY CORPORATION

8F., No. 653-2, Zhongzheng Rd., Xinzhuang Dist., New Taipei City 24257, Taiwan
sales@philio-tech.com Tel:+886-2-2908-8952 Fax:+886-2-29088652